

### **About the Poti Power Off Time parameter in the EZ-ZONE PM**

The **Poti** parameter is available in EZ-ZONE PM software beginning with Revision 9.00, and appears in the Global menu if the product has profiling with battery backup (i.e., a **B** or **E** in the 4th digit of the order code).

The purpose of this parameter is to set the amount of time that the controller will allow resumption of a running profile in the event of a power loss. The parameter has an allowable range of 0 (zero) to 9999 seconds.

If **Poti** is set to zero, then any power loss that occurs during a running profile will cause the profile to abort.

For values of **Poti** greater than zero seconds, a power loss that lasts less than the **Poti** setting will not abort a running profile; instead the controller will resume the profile at the point at which power was lost. If the power loss lasts longer than the **Poti** setting, then the running profile will be aborted.

When entering a non-zero value for **Poti**, the minimum value should be 30 seconds.

If the maximum time of 9999 seconds is entered, then if power is lost for more than 2 hours and 47 minutes, the running profile will be aborted.